Repeating Defects

To identify the component causing the defect, compare your print sample against the measurements shown.

To diagnose a defect on the transfer belt, print eight Letter/A4-size pages. Verify that the same defect appears on every fourth page.

Call for service for this defect.

Imaging Unit

43.6 mm (1.72 in.)

45 mm (1.77 in.)

94.5 mm (3.72 in.)

29.9 mm (1.18 in.)

23.2 mm (.91 in.)

Transfer Unit

37.7 mm (1.48 in.)

78.5 mm (3.09 in.)

54.6 mm (2.15 in.)

Fuser

95 mm (3.74 in.)

110 mm (4.33 in.)